MCR1 R02 - Single RS232C Cable - Product Code XP8923

For use with FarSync T-Series and X.PORT products

The twisted pairs within the cable to be utilised as follows. The pairings are as viewed on the 37 pin connector:

14-22, 15-23, 19-25, 24-29, 33-34.

Physical Layout

```
CARD CONNECTOR
   37 Pin ———————————————— 25 Pin
    Male                    Male

          <--- 1 metre --->
```

Single RS232C Cable:- Pin Connections for Ports

```
CARD CONNECTOR
   37 pin              25 pin
    male                male

                        Port A

     1 ———————————— 1      Shield
┌ 13
│ 14 ———————————— 2      TxD
│ 15 ———————————— 4      RTS
│ 19 ———————————— 20     DTR
│ 22 ———————————— 3      RxD
│ 23 ———————————— 5      CTS
│ 24 ———————————— 17     RxCi
│ 25 ———————————— 8      DCD
│ 29 ———————————— 15     TxCi
└ 31
  33 ———————————— 6      DSR
  34 ———————————— 22     RI
  37 ———————————— 7      signal ground
```

Copyright © FarSite Communications Ltd, 1999-2001
www.farsite.co.uk